

Stay healthy with iO₂

- Dual OLED display, 6 display modes
- Quick and spot-check of pulse rate and oxygen saturation
- Automatic power off in 10 seconds
- Small dimension, light weight
- Readable from ant angle
- Low power consumption
- Fits Pediatric and Adult
- Low power indication



iO₂ Fingertip Pulse Oximeter

Enjoy your life with iO₂

Technical Specifications

Display type:	Dual OLED display
SpO ₂ Measurement range:	70-100%
Accuracy:	high: 100, Low: 90
SpO ₂ alarm limit:	±2 at 70-100%
Pulse rate Measurement range:	30-250 BPM
Accuracy:	±2% BPM
Pulse Intensity:	Bargraph Indicator
Pulse rate alarm limit:	high: 120, low: 60
Power Requirement Battery:	Two AAA alkaline batteries
Power consumption:	Less than 60 mA
Low power indication Battery life:	Up to 15 hours
Dimension: Weight:	71.99(L) *36.84(W)*35.8(H) mm 42g (without battery)
Environmental Operation temperature:	0-45°
Storage temperature:	-10 to 50°



Economical, easy to use

Fast, reliable and accurate

Perfect choice for any health care practitioner

Standard Configurations

1. iO₂ fingertip oximeter main unit
2. Hanging Strap
3. Alkaline batteries
4. User manual



UTech Co., Ltd.

No.B-1, Jinshan International Industrial City, No.18 Nishang Road,
401120 Yubei District, Chongqing.

Tel: 86-23-88651832 Fax: 86-23-88651851
www.chinautec.com lily@chinautec.com.cn



ISO 13485:2003